


Producent falownika	Rodzaj	Komunikacja	Zineric F2	Zineric O1&O2
	SUN-SG01LP1 series	CAN	90% tested	✓
	SUN-SG03LP1 series	CAN	90% tested	✓
	SUN-SG04LP1 series	CAN	90% tested	✓
	SUN-SG04LP3 series	CAN	90% tested	✓
	CW-BP	CAN		✓
	SBP GW-ES	CAN		✓
	EM	CAN		✓
	S5-EA1P3K-L	CAN	✓	✓
	S6-EA1P(3.6-6)K-L	CAN	✓	✓
	S6-EO1P(4-5)K-48	CAN	✓	✓
	S5-EH1P(3-6)K-L	CAN	✓	✓
	S6-EH1P(3-6)K-L-EU	CAN	✓	✓
	SI 4.4-M	CAN		✓
	SI 6.0-H	CAN		✓
	SI 8.0-H	CAN		✓
	SI 6048US	CAN		✓
	ME3000SP	CAN		✓
	HYD series	CAN		✓
	HYS-LV Series	CAN		✓
	HAS-LV Series	CAN		✓
	Multiplus 48V (via Venus OS)	CAN		✓
	Quattro 48V (via Venus OS)	CAN		✓



Producent falownika		Rodzaj	Komunikacja	Zineric F2	Zineric O1&O2
		PLENTICORE plus	CAN		✓
		PLENTICORE plus G2	CAN		✓
		PLENTICORE BI xx/26	CAN		✓
		PLENTICORE BI xx/26 G2	CAN		✓
		PLENTICORE G3	CAN		✓
		SPH 3000 - 10000	CAN		with Cerbo GX
		SPF 2000 - 5000	CAN		with Cerbo GX
		SPF 5000 ES / SPF 6000 ES PLUS	CAN		✓
		WIT	CAN		✓
		T-REX-4-6KLP3G01 (4-6 kW)	RS485	✓	✓
		T-REX-10KLP3G01	RS485	✓	✓
		T-REX-3K6P1G01	RS485	✓	✓
		ASW3000-6000H-S2	CAN		✓

Ułożenie kabli w pinach do komunikacji z falownikami

NO.	Deye	Goodwe	Solis	Sungrow	Afore	Sofar	Hoymiles	Victron	Felicity
PIN 1	X	X	X	X	X	CAN_H	X	X	X
PIN 2	X	X	X	X	X	CAN_L	X	X	X
PIN 3	X	X	X	X	X	X	X	X	CAN_L
PIN 4	CAN_H	CAN_H	CAN_H	CAN_H	CAN_H	X	CAN_H	X	CAN_H
PIN 5	CAN_L	CAN_L	CAN_L	CAN_L	CAN_L	X	CAN_L	X	X
PIN 6	X	X	X	X	X	X	X	X	X
PIN 7	X	X	X	X	X	X	X	CAN_H	X
PIN 8	X	X	X	X	X	X	X	CAN_L	X

Powyższa dane są jedynie podglądowe. Kompatybilność może się zmieniać w dowolnym czasie. Jest to zależne od producentów falowników, więc niektóre dane mogą być nieaktualne, w zależności od momentu wydruku katalogu.



Kontakt:

Dział Handlowy:
zineric@zineric.com

Serwis Polska:
serwis@zineric.pl